

QUICKSTART GUIDE Polycom VVX-300/310/311



Business Telephone Solutions


For any questions, concerns, suggestions or support contact us at 705-675-0516 or 1-855-232-2322 **agilisnet.com**

QUICKSTART GUIDE *Polycom Vvx-300/310*



Features	Method
External Call:	Dial number 🔶 Press: 'Dial'
Internal Call:	Dial extension> Press: 'Dial'
Place Call on Hold:	Press: 'Hold' button
Park Call:	Press: 'Park' soft-key OR Press: ##
Answer Parked Call:	Dial parking lot number of the parked call
Anonymous Call:	Dial *67 → Dial number → Press: 'Dial'
Record Call:	Press: 'Record' soft-key OR Press: #1
Voicemail:	Press: 'Messages' button OR Dial: *98
Enable Call Forwarding:	Dial *72 -> Enter forwarding number -> Press: #
Disable Call Forwarding:	Dial *73
Log-in Extension:	Dial *11 \rightarrow Enter extension # \rightarrow Enter password
Log-out Extension:	Dial *12
Reboot Phone:	Dial 'Menu' → Settings → 1 → 8
DND:	Press: 'DND' soft-key





Transfer Attended:	Transfer Blind:	Conference:	Speed Dial:	Remote Voicemail	Voicemail Greetings:
1. While on a call, press the 'Xfer' button.	1. While on a call, press the 'Xfer' button.	 You must already be on a call. Press the 'Conf' Softkey and dial 	1. Dial: 00 2. Enter speed dial entry followed	Access: 1. Dial into system and dial extension number.	Busy Greeting - Heard when callers reach the voicemail and you are on another call.
 2. Dial the number to transfer to and press 'Dial'. 3. To transfer the call, press the 'Xfer' button. 	2. Dial the number to transfer to and press the 'Xfer' button.	the number you would like to add. 3. Upon connecting with second person, press 'Conf' Softkey again to connect all three parties.	by the pound key. 3. Enter the number to be assigned to this speed dial followed by the pound key.	2. When the greeting begins, press the * button and enter passcode when instructed.	Unavailable Greeting - Heard when calls to your extension are not answered.
			4. Listen for 'Speed Dial Saved' confirmation recording.		Temporary Greeting - Heard when this greeting is activated using option 3 then 4 from the main voicemail menu.